



# **CEILING MOUNT OCCUPANCY SENSOR**

LINE VOLTAGE

# **OVFRVIEW**

The SENSORWORX® family of line voltage ceiling mount occupancy sensors provides a compact control solution capable of switching lighting loads without requiring a powerpack. SENSORWORX products utilize the latest passive infrared technology and digital signal processing techniques to provide unmatched detection performance. Additionally SENSORWORX units are available with an integrated microphone to provide overlapping passive acoustic occupancy detection for rooms with obstructions.

# BASIC OPERATION

Sensors detect movement in the infrared energy that radiates from occupants as they move within the devices field-of-view. Once occupancy is identified, the sensor's internal relay switches power on to the connected lighting. If equipped with passive acoustic detection, the unit's microphone is then also enabled to further enhance detection while the lights are on. An internal timer is set to keep lights on during brief periods of inactivity, and is reset every time occupancy is signaled by either the passive infrared or acoustic detection technologies. Additionally, optional daylight detection is available that will turn off controlled lighting whenever there is sufficient ambient light in the space.

# APPLICATIONS

Line voltage sensors are self-contained units that directly power from and switch 120/277 VAC. Typically they are used to control areas where a single sensor's coverage area is sufficient for the entire space.

- Private Restrooms
- Small Offices
- Conference Rooms
- Copy Rooms Vestibules
- Break Rooms Walk-In Closets



**SPECIFICATIONS** 

**FEATURES** 

Detection

(optional)

Digital Passive Infrared (PIR)

Passive Acoustic Detection

360° Coverage Pattern

Field Changeable Lens

Project:

Date

- Compact Size and Matte Finish
- Convenient Test Mode and **Adjustable Time Delays**
- Electronically Timed Switching **Designed for LED Fixture Control**
- Optional Ambient Light Override (Photocell)

### **ELECTRICAL**

**OPERATING VOLTAGE** MVOLT (120-277 VAC)

LOAD RATINGS 800W @ 120 VAC 1200W @ 277 VAC

LOAD TYPES Tungsten Ballast I FD

### **ENVIRONMENTAL**

**OPERATING TEMP** -10° to 122°F (14° to 50°C)

**RELATIVE HUMIDITY** 0-95% Non-Condensing.

Indoor Use Only

### CODE COMPLIANCE

Sensors can be used to meet ASHRAE 90.1, IECC, & Title 24 energy code requirements

### PHYSICAL

SIZE 4.00" Diameter x 1.25" H (10.16 x 3.17 cm)

WEIGHT 4.75 oz

COLOR White

MOUNTING STYLE Mud Ring w/ 2.75" Spaced Ears 3.5" Trade Size Octagon Box

### **OPERATION**

TIME DELAYS 30 sec to 30 min 10 Minute Default

**TEST MODE** 5 sec

### **OTHER**

LISTINGS UL/CUL









COMPLIANT 24 20





# COVERAGE PATTERNS

### **PASSIVE INFRARED (PIR)**

- 8 to 15 ft (2.44 to 4.57 m) mounting height recommended
- Detection range improves when walking across beams as compared to into beams
- Lenses can be swapped in field if necessary, contact technical support for assistance

#### **SMALL MOTION 360°**

Best choice for detection of small motions from sitting occupants (e.g., hand motion)





#### LARGE MOTION 360°

- Best choice for detection of larger motion (e.g., walking)
- ~2000 ft<sup>2</sup> of coverage
- Longest segment of coverage pattern aligns with screw hole axis on sensor (shown as dotted line on Top View diagram below)



#### **DUAL TECHNOLOGY (PIR/ACOUSTIC)**

- Units with dual technology (SWX-221-2 and SWX-222-2) have overlapping acoustic detection of the complete PIR coverage area
- A PIR event is required to initially enable acoustic detection
- Sounds indicating occupancy reset the sensor's time delay while non-occupant noises are filtered out
- Occupant sounds alone will not keep lights on indefinitely, PIR motion must be periodically detected for lights to remain on for an extended time
- After sensor time out expires, acoustic detection remains enabled for 10 seconds to enable voice reactivation of lights for additional convenience and safety

#### **PHOTOCELL OPERATION**

Sensors with an integrated photocell will turn lights on/off depending on the amount of ambient light detected. This operation makes them ideal for lighting near skylights or windows.

## ORDERING INFO

#### SAMPLE MODEL # SWX-231-2

	PRODUCT		DETECTION		COVERAGE		VOLTAGE		ENVIRONMENT	
SWX	Ceiling Mount Sensor -	-2	PIR PIR + Daylight Dual Tech (PIR + Acoustic) Dual Tech + Daylight (PIR + Acoustic + Daylight)	0 1 2 3	Small Motion / Standard Range Large Motion / Extended Range	1 2	MVOLT (120/277 VAC)	-2	Standard Environment High Humidity Environment	Blank -HE

## WIRING



# INSTALLATION OPTIONS



